

Quantity per Pack: 10 pcs

**8x32**



Rated Current	Part Number Without Indicator	Part Number With Indicator	Watts Loss (W)	Voltage (AC)	Breaking Capacity (kA)
1	C08M1	C08M1I	0.11	400V	20 kA
2	C08M2	C08M2I	0.14		
4	C08M4	C08M4I	0.25		
6	C08M6	C08M6I	0.28		
8	C08M8	-	0.43		
10	C08M10	C08M10I	0.45		
12	C08M12	C08M12I	0.50		
16	C08M16	C08M16I	0.55		
20	C08M20	C08M20I	0.58		
25	C08M25	-	0.62		

**10x38**



Rated Current	Part Number Without Indicator	Part Number With Indicator	Watts Loss (W)	Voltage (AC)	Breaking Capacity (kA)
0.16	C10M0.16	-	0.24	500V	120 kA
0.25	C10M0.25	-	0.36		
0.5	C10M0.5	-	0.49		
1	C10M1	C10M1I	0.10		
2	C10M2	C10M2I	0.18		
4	C10M4	C10M4I	0.31		
6	C10M6	C10M6I	0.32		
8	C10M8	C10M8I	0.52		
10	C10M10	C10M10I	0.55		
12	C10M12	C10M12I	0.63		
16	C10M16	C10M16I	0.92	400V	
20	C10M20	C10M20I	0.96		
25	C10M25	C10M25I	1.40		
32	C10M32	C10M32I	1.80		

**14x51**



Rated Current	Part Number Without Indicator	Part Number With Indicator	Watts Loss (W)	Voltage (AC)	Breaking Capacity (kA)
0.25	C14M0.25	-	0.41	690V	80 kA
0.5	C14M0.5	-	0.69		
1	C14M1	C14M1I	0.14		
2	C14M2	C14M2I	0.24		
4	C14M4	C14M4I	0.45		
6	C14M6	C14M6I	0.42		
8	C14M8	C14M8I	0.70		
10	C14M10	C14M10I	0.53		
12	C14M12	C14M12I	0.88		
16	C14M16	C14M16I	1.16		
20	C14M20	C14M20I	1.23	500	120 kA
25	C14M25	C14M25I	1.46		
32	C14M32	C14M32I	2.04		
40	C14M40	C14M40I	3.34	400	
50	C14M50	C14M50I	304		

**22x58**



Rated Current	Part Number Without Indicator	Part Number With Indicator	Watts Loss (W)	Voltage (AC)	Breaking Capacity (kA)
2	C22M2	C22M2I	0.29	690V	80 kA
4	C22M4	C22M4I	0.48		
6	C22M6	C22M6I	0.47		
8	C22M8	C22M8I	0.73		
10	C22M10	C22M10I	0.74		
12	C22M12	C22M12I	0.83		
16	C22M16	C22M16I	1.21		
20	C22M20	C22M20I	1.29		
25	C22M25	C22M25I	1.53		
32	C22M32	C22M32I	2.13		
40	C22M40	C22M40I	3.40		
50	C22M50	C22M50I	3.48		
63	C22M63	C22M63I	4.46	400V	
80	C22M80	C22M80I	5.86		
100	C22M100	C22M100I	6.61		
125	C22M125	C22M125I	8.42		