

### ProLume

## Electronic Linear Fluorescent Ballast Specifications

Ballast Type: Electronic Fluorescent  
 Starting Method: Instant Start  
 Lamp Connection: Parallel  
 Input Voltage: 120V  
 Input Frequency: 60Hz

Lamp Type	# of Lamps	Volts	Rated Lamp Watts	Min. Start Temp (°F/°C)	Input Current (Amps)	Input Power (Watts)	Ballast Factor	THD %	Power Factor	B. E. F.	Wire Diag.
F32T8	2	120	32	0/-18	0.80	54	0.85	<130	56	1.59	2-17
F32T8	1	120	32	0/-18	0.55	34	1.03	<155	52	3.04	1-3
F25T8	2	120	25	0/-18	0.65	43	0.84	<140	54	1.97	2-17
F25T8	1	120	25	0/-18	0.46	27	1.01	<170	50	3.79	1-3
F17T8	2	120	17	0/-18	0.52	31	0.86	<160	51	2.77	2-17
F17T8	1	120	17	0/-18	0.35	20	1.05	<190	45	5.25	1-3
F40T8	1	120	40	32/0	0.62	40	0.99	<145	53	2.49	1-3

Also operates equivalent U-shaped lamps.  
 For residential use only.

#### WIRING DIAGRAMS

#### STANDARD LEAD LENGTHS

	in.	cm.
Black	22	63.50
White	22	63.50
Blue	31	78.74
Red	46	121.92

OCV: 600V

#### CASE DIAGRAM

#### CASE DIMENSIONS

Overall (L)	Width (W)	Height (H)	Mounting (M)
9.50"	1.30"	1.10"	8.90"

#### HOT SPOT LOCATION

Maximum Case Temperature: 194°F

Actual performance can vary depending on operating conditions. Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.

PN# 50118

