

# WAC LIGHTING

Responsible Lighting®






# Remote Transformers

1W Minimum Load



## Class 2 Enclosed Electronic Transformers

- Secondary wiring for Class 2 transformers does not require conduit sheathed cable or clamp wiring techniques
- Intrinsically safe, Class 2 transformers permit no greater than a 5 amp current be drawn
- Non-metallic sheathed cable may be used for secondary wiring in walls and ceilings
- Drop down to a smaller gauge wire if space in fixture does not permit secure connection directly with the non-metallic sheathed cable
- Powers most cabinet fixtures
- All transformers are UL Listed

	Model	Input	Output	Min Load	L	W	H	
	<b>EN-1260-RB2</b>	120V	12V, 60W	1W	6½"	1⅝"	1¼"	<i>Fits through small openings</i>
	<b>EN-2460-RB2</b>	120V	24V, 60W	1W	6½"	1⅝"	1¼"	
	<b>EN-24100-RB2</b>	120V	24V, 96W	1W	6½"	1⅝"	1¼"	
	<b>EN-12120-RB2</b>	120V	12V, 2 × 60W	1W	6"	3¼"	2⅝"	<i>Includes LED indicator lights and integral push in terminals</i>
	<b>EN-12180-RB2</b>	120V	12V, 3 × 60W	1W	6¾"	3⅝"	2⅝"	
	<b>EN-12300-RB2</b>	120V	12V, 5 × 60W	1W	8½"	4⅝"	2⅝"	
	<b>EN-1260-P-AR-BK</b>	120V	12V, 60W	1W	2¾"	1⅝"	1¼"	<i>Plug-in power supply with on/off switch and 6' detachable cord</i>
	<b>EN-1260-P-AR-WT</b>	120V	12V, 60W	1W	2¾"	1⅝"	1¼"	
	<b>EN-2460-P-AR</b>	120V	24V, 60W	1W	2¾"	1⅝"	1¼"	



## Enclosed Electronic Transformers

- Use for all initial installations to ensure safe and primary side connections in a wiring compartment
- Dim with Electronic Low Voltage (ELV) dimmers




	Model	Input	Output	Min Load	L	W	H	
	<b>EN-1260-RB-AR</b>	120V	12V, 60W	1W	6½"	1⅝"	1¼"	<i>Enclosure has separate compartments for transformer, line and low voltage wiring</i>
	<b>EN-1275-RB-AR</b>	120V	12V, 75W	1W	6½"	1⅝"	1¼"	
	<b>EN-12100-RB-AR</b>	120V	12V, 100W	1W	6¼"	3"	1⅝"	<i>Includes LED indicator lights and integral push in terminals</i>
	<b>EN-12150-RB-AR</b>	120V	12V, 150W	1W	6¼"	3"	1⅝"	
	<b>EN-24150-RB-AR</b>	120V	24V, 150W	1W	6¼"	3"	1⅝"	
	<b>EN-B12PY-AR</b>	120V	12V, 250W	1W	6¼"	3⅜"	2⅝"	
	<b>EN-B24PZ-AR</b>	120V	24V, 300W	1W	6¼"	3⅜"	2⅝"	

## Non-Enclosed Electronic Transformers

- UR (UL ready) components
- All connections must be made in an enclosure for proper installations

	Model	Input	Output	Min Load	L	W	H	
	<b>EN-1260-R2*</b>	120V 50/60Hz	12V, 60W	1W	2⅝"	1⅜"	1"	<i>Designed to be used as a replacement part for factory installed transformers or installed in a properly listed enclosure</i>
	<b>EN-1260-R-AR</b>	120V 50/60Hz	12V, 60W	1W	2⅝"	1⅜"	1"	
	<b>EN-1275-R-AR</b>	120V 50/60Hz	12V, 75W	1W	2⅝"	1⅜"	1"	
	<b>EN-12100-R-AR</b>	120V 50/60Hz	12V, 100W	1W	3½"	1½"	1⅝"	
	<b>EN-12150-R-AR</b>	120V 50/60Hz	12V, 150W	1W	3½"	1½"	1⅝"	
	<b>EN-24150-R-AR</b>	120V 50/60Hz	24V, 150W	1W	3½"	1½"	1⅝"	

\*U.L. Listed Class 2 Component

Enclosures	Model	L	W	H		Multiple Terminal Block	L	W	H	
	<b>ETB</b>	6¼"	3"	1⅝"	<i>Holds one EN-12100-R-AR, EN-12150-R-AR or EN-24150-R-AR</i>		<b>MTB-01</b>	3¼"	1¾"	⅞"
	<b>METB</b>	6⅝"	1⅝"	1⅝"	<i>Holds one EN-1260-R-AR, EN-1275-R-AR or EN-1260-R2</i>	<p>12.5A max accommodates up to 6 output connections for 14 AWG wires. Terminal block is used to easily wire together multiple output connections for a neat under cabinet installation without the use of open splices. Perfect for wiring up to 3 button lights at 20W or 6 button lights at 10W.</p>				