

# 72300 - GEM400ML5AA4-5

### GE HID Distributor Replacement Kit Magnetic Core & Coil Ballast

- · Magnetic ballast construction ideal for a wide variety of lighting applications.
- Precision-wound coils, ensuring even heat dissipation and the highest electrical integrity.
- Distributor replacement kit contains the appropriate core & coil with color coded leads, a properly rated capacitor
- and ignitor (if required) and all other components required for ballast replacement
- Multi-5 ballast (120, 208, 240, 277, or 480 Volt) featuring a 480-Volt tap.





#### **CAUTIONS & WARNINGS**

#### Warning

- Risk of Electric Shock
- Properly ground ballast and fixture.
- Turn power off before servicing--see instructions.

#### NOTES

• Kit contains the appropriate core & coil with color coded leads, a properly rated capacitor and ignitor (if required) and all other components required for ballast replacement

## **GENERAL CHARACTERISTICS**

HID -Lamp Type Bulb Magnetic Ballast Type Core & Coil Replacement kit Туре 10.0 % Line Voltage Regulation (+/-) Ballast Factor Normal Circuit Type CWA Insulation Class 180C Enclosure Type None 24.0 µF Capacitance Capacitor Temperature Rating 100.0 °C

### **ELECTRICAL CHARACTERISTICS**

Supply Current Frequency	60.0 Hz
Voltage (MIN)	360.0

## DIMENSIONS

V

Weight	12.5 lb
Exit Type	
Diameter	1.750 in(44.4 mm)
Nominal Length	3.750 in(95.2 mm)
Frame size (H x L)	NaN in(NaN mm)

## **PRODUCT INFORMATION**

Product Code Description Standard Package Standard Package GTIN Standard Package Quantity Sales Unit No Of Items Per Sales Unit No Of Items Per Standard Package UPC

72300 GEM400ML5AA4-5 Master 10043168723005 3 **Distributor Kit** 1 3

043168723008