

## Accessories Landscape Accessory Landscape

alog	Black	Gauge	Dimens	sions (Inches)	
	Finish		P8699		
			P8635		
			P8628		
			P8626		
			P8617		
				-31	
				Туре	_

			. 6633		
Catalog	Black	 Gauge	Dimensions (Inches)		
No.			Length	Width	
P8617	-31	14	900	1/4	
P8626	-31	14	1800	1/4	
P8628	-31	12	1200	1/4	
P8635	-31	10	3600	3/8	
P8699	-31	12	2400	3/8	



## **Specifications:**

## General

- Recommended for use with P8270-31 transformer and LED Lighting. Low voltage cable runs from P8270-31 control center down path of lighting. UV protected, burial is not required, hide with ,ulch if desired. Perfect fit with fixture connectors for easy installation.
- 14 Gauge note: 150' is the max. run distance from transformer location to assure best fixture operation

## <u>Labeling</u>

• UL listed

Progress Lighting
Post Office Box 5704
Spartanburg, South Carolina
29304-5704