TRUE RMS AUTORANGING MULTIMETER

This True RMS multimeter provides the durability, accuracy and performance needed for the professional user. Features include a rugged IP67 waterproof and dust proof housing, CAT IV safety rating and 1000 volt input protection.



southwiretools.com





Model # 12070T

FEATURES

- True RMS for accurate measurements of non-linear loads
- Rugged design with waterproof/dust proof housing and 1000V input protection
- Capacitance, Frequency and Temperature functions
- Impact resistant double molded housing also provides comfortable grip
- IP67, dustproof and waterproof
- CAT IV 600V, CAT III 1000V

SPECIFICATIONS

TRUE RMS AUTORANGING MULTIMETER

INCLUDES

- 12070T Multimeter
- Test leads
- Type K temperature probe with banana plug adapter
- Magnetic hanging strap
- 9 volt battery

TRUE RMS AUTO-RANGE MULTIMETER (12070T)			
	Range	Max. Resolution	Basic Accuracy (% of reading)
AC Voltage:	1000V	0.1mV	±1.0%
DC Voltage:	1000V	0.1mV	±0.5%
AC Current:	10A	0.1µA	±1.0%
DC Current:	10A	0.1µA	±0.8%
Resistance:	40ΜΩ	0.1Ω	±0.8%
Capacitance:	40mF	10pF	±3.0%
Frequency:	10MHz	0.001Hz	±1.0%
Temperature:	-4 to 1400°F -20 to 760°C	0.1 °F 0.1°C	±3.0%
Continuity:	Audible threshold: Approximately 30Ω		
Diode Test:	Yes		
Dimensions:	6.70 x 3.11 x 1.97 in.		
Weight:	680g		





^{© 2013} Southwire Company. All Rights Reserved. @ Registered Trademark or TM Trademark of Southwire Company. Southwire provides a hassle-free warranty program for all Electrician Tools and Contractor Equipment by Maxis.